

Re-burn a Single User USB Hardware Lock for AHGW

Applies to AHGW versions: 3.x Please contact Aquaveo for help with other versions

We're here to help – Please contact us with any questions

Sales & Billing: Technical Support: +1(801) 691-5528 +1(801) 691-5530 sales@aquaveo.com support@aquaveo.com

www.aquaveo.com



- 1. Plug the Aquaveo hardware lock into a computer with hardware lock drivers and AHGW installed.
- 2. Start ArcMap and ensure that the AHGW Toolbar is visible by right-clicking in the toolbar area and checking **Arc Hydro Groundwater Toolbar**.
- 3. Locate the **Help** drop-down menu from the AHGW Toolbar and select **Register**.

Q Untitled - ArcMap - ArcView	
File Edit View Bookmarks Insert Selection Geoprocessing	Customize Windows Help
: 🗅 🖆 🖨 🐁 🖄 🛍 🗶 🗠 🍽 🗠 🗌	
🕴 Arc Hydro GW 🔻 Subsurface 🕶 💷 🔝 🏦 🏥 💺 📔 Field	- Help)

4. In the Register AHGW dialog, click the **Change Registration...** button.

O Register AHGW 3.1		
Show only enabled modules		
Components Status		
Password:		
License expires: N/A		
Maintenance expires: N/A		
Hardware lock: None		
License expires: N/A		
Maintenance expires: N/A		
Change Registration		
Help Show Log Close		



5. Select **Hardware lock** for the Licensing method and click the **Next** > button.

Registration Wizard - Step 1	×
Licensing method Hardware lock License code*	ſ
Request Evaluation License* Buy Software* * Requires an internet connection	
Security string: 0 2816729en	
Contact info	
For questions or support contact Aquaveo:	
license@aquaveo.com	
801-302-1400	
http://www.aquaveo.com/contact-us	
< Back Next > Cance	



6. In the Hardware lock options, select **Modify lock on this computer** with the follow code and click the **Next** > button.

Registration Wizard - Step 2
Hardware lock options C Get license from a single user lock. C Get license from a network lock. Modify lock on this computer with following code (uses internet): <u>HWE61IG</u> C Setup Sentinel Server for network locks.
Network lock setting
C IP address Browse Lock Setting C Host name
Apply Lock Setting
< Back Next > Cancel



7. In the Hardware Lock dialog, click the **Next** > button to burn the hardware lock.

Hardware Lock	×
This will burn one single-user lock. Press Next to continue.	
	NOTE: Burning the hardware lock may take a few seconds. Please be patient during this process and wait for the confirmation before unplugging the lock.
	< Back Next > Cancel



8. If the registration is successful, click **Finish** to exit the Registration Wizard.

Registration Wizard - Step 3			×
- Status Registration successful. Press Finish to see enab	oled components.		
	< Back	Finish	Cancel



9. The Register AHGW dialog indicates the registered components, the licensing method, and the license expiration dates.

Register AHGW 3.1		
Show only enabled modules		
Components	Status	
Arc Hydro GW	Enabled	
MODFLOW Analyst	Enabled	
Subsurface Analyst	Enabled	
Password: License expires: N/A Maintenance expires: N/A Hardware lock: SN:1474 License expires: Never		
Maintenance expires: 17 Nov 2016		
Change Registration		
Help	Show Log Close	